

TN-5308-4/8PoE Series Quick Installation Guide

M12 unmanaged PoE ToughNet switch

Edition 5.0, February 2017

Technical Support Contact Information www.moxa.com/support

Moxa Americas:

Toll-free: 1-888-669-2872

Tel: 1-714-528-6777

Fax: 1-714-528-6778

Moxa China (Shanghai office):

Toll-free: 800-820-5036

Tel: +86-21-5258-9955

Fax: +86-21-5258-5505

Moxa Europe:

Tel: +49-89-3 70 03 99-0

Fax: +49-89-3 70 03 99-99

Moxa Asia-Pacific:

Tel: +886-2-8919-1230

Fax: +886-2-8919-1231

Moxa India:

Tel: +91-80-4172-9088

Fax: +91-80-4132-1045



© 2017 Moxa Inc. All rights reserved.

P/N: 1802053080023



Overview

The ToughNet TN-5308-4PoE and TN-5308-8PoE series M12 unmanaged PoE Ethernet switches are designed for industrial applications in harsh environments. The TN series switches use M12 connectors to ensure tight, robust connections, and guarantee reliable operation against environmental disturbances, such as vibration and shock. The TN-5308-4PoE and TN-5308-8PoE series Ethernet switches provide 8 Fast Ethernet M12 ports, 4 or 8 of which are 10/100BaseT(X) PoE compliant, support IEEE 802.3/802.3u/802.3x/802.3af with 10/100M, full/half-duplex, MDI/MDI-X auto-sensing, and provide an economical solution for your industrial Ethernet network.

TN-5308-4PoE and TN-5308-8PoE switches provide up to 15.4 watts of power per PoE port, and allow power to be supplied to connected devices (such as surveillance cameras, wireless access points, and IP phones). Models with an extended operating temperature range of -40 to 75°C are also available. The TN-5308-4PoE/8PoE series Ethernet switches comply with a portion of EN 50155 specifications, covering operating temperature, power input voltage, surge, ESD, and vibration, making the switches suitable for a variety of industrial applications.

Package Checklist

Your TN-5308-4PoE or TN-5308-8PoE is shipped with the following items. If any of these items is missing or damaged, please contact your customer service representative for assistance.

- Moxa ToughNet Switch
- Panel Mounting Kit
- Quick installation guide (printed)
- Warranty card

Features

High Performance Network Switching Technology

- 8 10/100BaseT(X) ports, including 4/8 PoE ports providing up to 15.4 watts per port.
- Store and Forward switching process type.
- IEEE 802.3/802.3u/802.3x.
- 10/100M, Full/Half-Duplex, MDI/MDIX auto-sensing.


Industrial-Specific Applications

- Support 48 VDC (46 to 50 VDC) power input.
- Intelligent PD power consumption detection and classification.
- Active circuit protection.

Rugged Design


- M12 circular connector for vibration-resistant robust connections.
- Operating temperature range of -25 to 60°C, or extended operating temperature range of -40 to 75°C for "-T" models.
- IP40, rugged metal housing.
- Panel mounting or DIN-rail mounting installation capability.

TN-5308-4PoE Panel Layouts



1. TP port's 10/100 Mbps LED
2. 10/100BaseT(X) port
(female 4-pin shielded M12 connector with D coding)
3. Port label
4. Screw holes for panel mounting kit or DIN rail mounting kit
(there are 3 holes: top middle, bottom left, and bottom right)
5. Power input LED
6. Power input port
(male 5-pin shielded M12 connector with A coding)
7. Grounding screw
8. Power input port pin assignment
9. Model name
10. TP port pin assignment
11. Model label
12. 10/100BaseT(X) PoE port
(female 4-pin shielded M12 connector with D coding)
13. PoE port's LED


TN-5308-8PoE Panel Layouts




1. TP port's 10/100 Mbps LED
2. 10/100BaseT(X) port
(female 4-pin shielded M12 connector with D coding)
3. Port label
4. Screw holes for panel mounting kit or DIN rail mounting kit
(there are 3 holes: top middle, bottom left, and bottom right)
5. Power input LED
6. Power input port
(male 5-pin shielded M12 connector with A coding)
7. Grounding screw
8. Power input port pin assignment
9. Model name
10. TP port pin assignment
11. Model label
12. 10/100BaseT(X) PoE port
(female 4-pin shielded M12 connector with D coding)
13. PoE port's LED

Mounting Dimensions (unit = mm)

TN-5308-4PoE



TN-5308-8PoE



Panel/Wall Mounting

Mounting the TN-5308-4/8PoE on the wall requires 3 screws. Please use the 3 screws packed in the panel mounting kit.

STEP 1: Prepare the 3 screw holes on the wall according to the positions of the 3 screw holes on the switch shown on the mounting dimension diagram.

STEP 2: Use one screw to go through the top-middle screw hole on the switch and screw it into the wall.

STEP 3: Screw in the remaining 2 screws through the bottom-left and bottom-right holes on the switch to the wall.


NOTE Please use the screws (M3 x 40 mm) packed in the panel mounting kit.

DIN-Rail Mounting (optional)

With the optional DIN-Rail mounting kit DK-TN-5308-4/8PoE (must be purchased separately), you can mount the TN-5308-4/8PoE on a 35mm DIN-Rail.


STEP 1:

Fix the DIN-Rail attachment plate onto the rear panel of the switch as shown in the figure at the right.




STEP 2:

Position the TN-5308-4/8PoE on the DIN-Rail, tilting to hook clamps over the top edge of the rail.



STEP 3:

Swing the switch down fully onto the DIN-Rail until both clamps completely latch.



To remove the Moxa ToughNet Switch from the DIN-Rail, simply reverse Steps 2 and 3 above.

Wiring Requirements



WARNING

Turn the power off before disconnecting modules or wires. The correct power supply voltage is listed on the product label. Check the voltage of your power source to make sure you are using the correct voltage. Do NOT use a voltage greater than what is specified on the product label.

These devices must be supplied by a SELV source as defined in the Low Voltage Directive 2006/95/EC and 2004/108/EC.



ATTENTION

Safety First!

Be sure to disconnect the power cord before installing and/or wiring your Moxa switch.

This device has UL508 approval. Use copper conductors only, 60/75°C, and tighten to 4.5 pound-inches. For use in pollution degree 2 environments.



ATTENTION

Safety First!

Calculate the maximum possible current in each power wire and common wire. Observe all electrical codes dictating the maximum current allowable for each wire size. If the current goes above the maximum ratings, the wiring could overheat, causing serious damage to your equipment.

Please read and follow these guidelines:

- Use separate paths to route wiring for power and devices. If power wiring and device wiring paths must cross, make sure the wires are perpendicular at the intersection point.
NOTE: Do not run signal or communications wiring and power wiring through the same wire conduit. To avoid interference, wires with different signal characteristics should be routed separately.
- You can use the type of signal transmitted through a wire to determine which wires should be kept separate. The rule of thumb is that wiring that shares similar electrical characteristics can be bundled together.
- Keep input wiring and output wiring separated.
- It is strongly advised that you label wiring for all devices in the system when necessary.

Grounding the TN-5308-4/8PoE

Grounding and wire routing help limit the effects of noise due to electromagnetic interference (EMI). Run the ground connection from the grounding screw to the grounding surface prior to connecting devices.




ATTENTION


This product is intended to be mounted to a well-grounded mounting surface such as a metal panel.

Connecting the Power Supply

The M12 A-coded 5-pin male connector on the TN-5308-4/8PoE front panel is used for the DC power input. You have to prepare a power cord with M12 A-coded 5-pin female connector to connect the switch to the DC power input.

Pinouts for the power input port on the TN-5308-4/8PoE

PIN	PWR
1	V+
2	N.C.
3	V-
4	N.C.
5	



N.C. : Not connected

STEP 1: Plug your power cord connector to the power input port of the TN-5308-4/8PoE switch.

STEP 2: Screw the nut on your power cord connector to the power input connector on the switch to ensure a tight connection.



ATTENTION

Before connecting the TN-5308-4/8PoE to the DC power input, make sure the DC power source voltage is stable.

Connecting the Data Lines

10/100BaseT(X) Ethernet Port Connection

All TN-5308-4/8PoE models have 8 10/100BaseT(X) Ethernet ports (4-pin shielded M12 connectors with D coding). The 10/100TX ports located on the TN-5308-4/8PoE's front panel are used to connect to Ethernet-enabled devices. Most users configure these ports for Auto MDI/MDI-X mode, in which case the port's pinouts are adjusted automatically depending on the type of Ethernet cable used (straight-through or cross-over), and the type of device (NIC-type or HUB/Switch-type) connected to the port.

In what follows, we give pinouts for both MDI (NIC-type) ports and MDI-X (HUB/Switch-type) ports. We also give cable wiring diagrams for straight-through and cross-over Ethernet cables.

Pinouts for the 10/100BaseT(X) Ports on the TN-5308-4/8PoE


PIN	TX
1	TD+
2	RD+
3	TD-
4	RD-



Housing: Shield

Pinouts for the RJ45 (8-pin) Port

RJ45 (8-Pin)



MDI Port Pinouts

Pin	Signal
1	Tx +
2	Tx -
3	Rx +
6	Rx -


MDI-X Port Pinouts

Pin	Signal
1	Rx +
2	Rx -
3	Tx +
6	Tx -

M12 (4-pin, M) to M12 (4-pin, M) Cross-Over Cable Wiring




Cross-Over Cable Wiring



M12 (4-pin, M) to M12 (4-pin, M) Straight-Through Cable Wiring




Straight-through Cable Wiring



M12 (4-pin, M) to RJ45 (8-pin) Cross-Over Cable Wiring




Cross-Over Cable Wiring



M12 (4-pin, M) to RJ45 (8-pin) Straight-Through Cable Wiring



Straight-through Cable Wiring



Auto MDI/MDI-X Connection

The Auto MDI/MDI-X function allows users to connect TN-5308-4/8PoE's 10/100BaseTX ports to any kind of Ethernet device, without needing to pay attention to the type of Ethernet cable being used for the connection. This means that you can use either a straight-through cable or cross-over cable to connect the TN-5308-4/8PoE to Ethernet devices.

LED Indicators

Several LED indicators are located on the TN-5308-4/8PoE's front panel. The function of each LED is described in the table below.

LED	Color	State	Description
PWR	AMBER	On	Power is being supplied to the power input.
		Off	Power is not being supplied to the power input.
TP (10M)	AMBER	On	TP port's 10 Mbps link is active.
		Blinking	Data is being transmitted at 10 Mbps.
		Off	TP port's 10 Mbps link is inactive.
TP (100M)	GREEN	On	TP port's 100 Mbps link is active.
		Blinking	Data is being transmitted at 100 Mbps.
		Off	TP port's 100 Mbps link is inactive.
PoE	AMBER	On	Power is being supplied to the Powered Device (PD).
		Off	Power is not being supplied to the Powered Device (PD).

Auto-Negotiation and Speed Sensing

All of the TN-5308-4/8PoE's Ethernet ports independently support auto-negotiation for speeds in the 10BaseT and 100BaseTX modes, with operation according to the IEEE 802.3u standard. This means that some nodes could be operating at 10 Mbps, while at the same time, other nodes are operating at 100 Mbps.

Auto-negotiation takes place when an M12 cable connection is made, and then each time a LINK is enabled. The TN-5308-4/8PoE advertises its capability for using either 10 Mbps or 100 Mbps transmission speeds, with the device at the other end of the cable expected to advertise in the same way. Depending on what type of device is connected, this will result in agreement to operate at a speed of either 10 Mbps or 100 Mbps.

If a TN-5308-4PoE's Ethernet port is connected to a non-negotiating device, it will default to 10 Mbps speed and half-duplex mode, as required by the IEEE 802.3u standard.

Specifications

Technology	
Standards	IEEE 802.3 for 10BaseT IEEE 802.3u for 100BaseT(X) IEEE 802.3x for Flow Control IEEE 802.3af for Power-over-Ethernet
Processing Type	Store and Forward
Flow Control	IEEE802.3x flow control, back pressure flow control
Interface	
M12 Ports	10/100BaseT(X) auto negotiation speed, F/H duplex mode and auto MDI/MDI-X connection
LED Indicators	PWR, 10/100M
Power Requirements	
Input Voltage	48 VDC (46 to 50 VDC)
Input Current	TN-5308-4PoE: 1.6A @ 48 VDC TN-5308-8PoE: 2.9A @ 48 VDC
Connection	M12 A-coding, 5-pin male connector
Overload Current Protection	3 A @ 48 VDC
Reverse Polarity Protection	3 A @ 48 VDC
PoE (pre port)	
Max. Output Power	15.4 W
Output Voltage	44 to 48.5 VDC
Max. Output Current	350 mA
Max. Overload Protection	400 mA
Physical Characteristics	
Housing	Metal, IP40 protection
Dimensions (W x H x D)	TN-5308-4PoE: 60 x 216.6 x 49.5 mm (2.36 x 8.53 x 1.95 in) TN-5308-8PoE: 80 x 216.6 x 52.9 mm (3.15 x 8.53 x 2.08 in)
Weight	TN-5308-4PoE: 675 g (1.49 lb) TN-5308-8PoE: 970 g (2.14 lb)

Installation	Panel mounting, DIN-Rail mounting (with optional kit)
Environmental Limits	
Operating Temperature	Standard Models: -25 to 60°C (-13 to 140°F) Wide Temp. Models: -40 to 75°C (-40 to 167°F)
Storage Temperature	-40 to 85°C (-40 to 185°F)
Operating Humidity	5 to 95% (non-condensing)
Regulatory Approvals	
Safety	UL/cUL 508, EN 60950-1 (LVD)
EMI	FCC Part 15 Subpart B Class A, EN 55032 Class A
EMS	IEC 61000-4-2 ESD: Contact 6 kV; Air 8 kV IEC 61000-4-3 RS: 20 V/m (80 MHz to 1 GHz) IEC 61000-4-4 EFT: Power 2 kV; Signal 2 kV IEC 61000-4-5 Surge: Power 2 kV; Signal 2 kV IEC 61000-4-6 CS: 10 V IEC 61000-4-8
Rail Traffic	(for panel mounting installations) EN 50155*, EN 50121-4, EN 45545-2
*Complies with a portion of EN 50155 specifications.	
Shock	EN 50155, IEC 61373
Freefall	IEC60068-2-32
Vibration	EN 50155, IEC 61373
Note: Please check Moxa's website for the most up-to-date certification status.	
MTBF (mean time between failures)	
Time	TN-5308-4PoE-48 Series: 252,075 hrs. TN-5308-8PoE-48 Series: 308,392 hrs.
Standard	Telcordia SR332
Warranty	
Warranty Period	5 years
Details	See www.moxa.com/warranty

Patent http://www.moxa.com/doc/operations/Moxa_Patent_Marking.pdf