

# Eaton B29SRE45TA3E032

Catalog Number: B29SRE45TA3E032

Eaton definite purpose 1-phase starter, Non-reversing w/ C396, Separate ctrl, Open w/ DIN rail mount adapter, Lugs w/o quick connect terms, 45 A, 24 V coil, 1NO pressure plate, Std. C396 OLR, 24-32 A overload

## General specifications

Product Name	Catalog Number
Eaton definite purpose starter	B29SRE45TA3E032
UPC	Product Length/Depth
786685210025	6.67 in
Product Height	Product Width
13.27 in	7.64 in
Product Weight	Warranty
10.6 lb	1 year
Certifications	
UL Listed	
CSA Certified	



## Product specifications

### Contact configuration

1 NO pressure plate

### Inductive full load

45 A

### Overload range

24-32 A

### Phase

Single-phase

### OLr model designation

Std. C396 OLR

### Control characteristics

Separate control

### Enclosure

Open with DIN rail mounting adapter

### Amperage Rating

24 V, 50/60 Hz

### Coil

24 Vac

### Type

Non-reversing w/ C396

### Model

Starter

### Terminals

Lugs without quick connect terms

### Current range

45 A

## Resources

### Catalogs

[Lighting and Definite Purpose Control](#)

### Specifications and datasheets

[Eaton Specification Sheet - B29SRE45TA3E032](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com  
© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)