

Eaton V210M5CJC

Catalog Number: V210M5CJC

Eaton NEMA starter, B100 Series Manual Motor Starter, Provides Manual Control and Overload Protection, Includes a Three-pole Bimetallic Overload Relay, Field mounted Auxiliary Contacts, Lockout Device Standard, Two pole, Size M-1

General specifications



Photo is representative

Product Name

Eaton NEMA starter

UPC

782114114933

Product Height

4.9 in

Product Weight

1.85 lb

Certifications

UL Listed

CSA Certified

Catalog Number

V210M5CJC

Product Length/Depth

8.2 in

Product Width

6.2 in

Warranty

Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.

Catalog Notes

Starters use Type B overload relay. Heater Packs not included. Coils are rated for 50/60 Hz applications.

defaultTaxonomyAttributeLabel

Phase

Three-phase

Number of Poles

Three-pole

NEMA frame size

NEMA Size 5

Resources

Brochures

[Factory Service for Industrial Molded Case Circuit Breakers and Vacuum Contactors/Starters](#)

Catalogs

[Eaton's Volume 10—Enclosed Control](#)

Installation instructions

[Instructions for V200, V210, V250 NEMA Size 5, 3 Pole Vacuum Motor Controller Non-reversing or Reversing](#)

Specifications and datasheets

[Eaton Specification Sheet - V210M5CJC](#)

Warranty guides

[Selling Policy 25-000 - Distribution and Control Products and Services](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)