Grounding Kit



A Pentair Company

Hoffman Enclosures Inc. 2100 Hoffman Way 10-32 Anoka, MN 55303-1745 Ground Wire Hex Nut (763) 422-2211 Tel (Not Included) www.hoffmanonline.com Ground Connector Drill 7/32 inch diameter hole. d **Bottom End** of Enclosure Ground Label

NOTE: Only use this ground kit where the use of this component is specified.

- 1. Drill 7/32 inch diameter hole in the bottom end of enclosure.
- Remove paint where the ground connector will contact the enclosure to insure electrical continuity.
- 3. Install the ground connector and connect ground wire as shown.
- 4. Attach ground label adjacent to connector as shown.
- 5. If this enclosure has provisions for installing a panel, install the lockwasher included in the enclosure under one of the screws securing the panel. This will insure grounding between the panel and the enclosure.

Rev. A 103397

© 2002 Hoffman Enclosures Inc.

P/N 79208001

10-32x1 Screw

87568259



RSPSupply - 1-888-532-2706 - www.RSPSupply.com/p-6745-Hoffman-AG